

## YAGI Antenna - UHF

### YAGI antena - UHF

# DTX-92F

- ✓ **The antenna is especially designed for the digital terrestrial signal's (DVB-T) reception**  
*Antena je pripravljena za sprejem digitalnih zemeljskih signalov (DVB-T)*
- ✓ **Covers frequency range 470 - 862 MHz (Ch. 21-69).**  
*Pokriva frekvenčni pas 470 - 862 MHz (kanal 21-69).*
- ✓ **Impedance 75 Ohm.**  
*Impedanca 75 Ohm.*
- ✓ **Antenna carriers 18x18 mm.**  
*Nosilci antene 18x18 mm.*
- ✓ **Can be used for horizontal polarization. Vertical polarization is possible but not recommended.**  
*Primerna za horizontalno polarizacijo. Vertikalna polarizacija je mogoča, a jo ne priporočamo.*
- ✓ **Reliable and robust design for optimum performance and long life time.**  
*Zanesljiv in robusten dizajn za optimalno delovanje in dolgo življenjsko dobo.*



Type Tip	No. of elements Število elementov	Gain Dobitek	F/B ratio Razmerje napr.-naz.	Beam width Širina glav. lista	Antenna length Dolžina antene	Connection Priključek	Packing Pakiranje	
							pcs. kos	cm / m3 cm / m3
DTX-92 F	92	12 - 18,5 dB(i)	> 30 dB	H 50-26°	237 cm	"F"	1	124x33x9 / 0,037

**Antenna is assembled by two antenna carriers and additional support under carriers.**  
**Antena je sestavljena iz dveh nosilcev in opore pod tema nosilcema.**

